

Extract product line from Smart Home specifications

kabbellytta

June 3, 2009

1 Scenario SC 01

1.1 Description:

This scenario allows the home owner to register new inhabitants. In this way, the policies for getting access in the home are applied.

1.2 Related feature

Register Inhabitant

1.3 Flow of events

Code	Feature	User Action	System Response
SC 1.1	Register Inhabitant	The home owner selects the register inhabitant option in the security configuration menu.	The inhabitant personal form is displayed.
SC 1.1(A)	Password	The home owner fills in the inhabitant personal form and selects the proceed option.	The system asks for the inhabitant password (and password confirmation) that allows her to get access to the home.
SC 1.1(B)	Fingerprint	The home owner fills in the inhabitant personal form and selects the proceed option.	The system asks the inhabitant to capture her fingerprint.
SC 1.2(A)	Password	The new inhabitant fills in the password (and confirmation password) for getting access to the home.	The system verifies that the password and confirmation password are equal. The system asks the home owner to select the proceed option.
SC 1.2(B)	Fingerprint	The new inhabitant put her finger in the fingerprint reader.	The system captures the mark of the inhabitant fingerprint and asks the home owner to proceed.
SC 1.3	Register Inhabitant	The home owner selects the proceed option.	The system asks the home owner her configuration password.
SC 1.4	Register Inhabitant	The home owner fills in the configuration password and selects the proceed option.	The system register the new inhabitant, allowing she to get access to the smart house.

2 Scenario SC 02

2.1 Description:

Request access to the smart home

2.2 Related feature

Inhabitant Authorization

2.3 Flow of events

Code	Feature	User Action	System Response
SC02.1(A)	Password	The inhabitant request access to the home at the main entrance.	The system requests to the user to pass the smart card.
SC02.1(B)	Fingerprint	The inhabitant request access to the home at the main entrance.	The system asks the inhabitant to capture her fingerprint.
SC02.2(A)	Password	The inhabitant inserts the smart card into the card reader.	The system asks the inhabitant's password, in order to authorize her access to the smart home.
SC02.2(B)	Fingerprint	The new inhabitant put her finger in the fingerprint reader.	The system recognizes the fingerprint impression.
SC02.3	Inhabitant Authorization	-	The system displays the message of successful authorization.
SC02.3(A)	Password	The inhabitant informs her password.	The system verifies that the password is valid for the registered inhabitant.
SC02.4	Inhabitant Authorization	-	The system opens the front door and register the occurrence.
SC02.5	Inhabitant Authorization	-	After \$Time to Close, the front door is closed.

3 Scenario SC03

3.1 Description:

Guest request access to the smart home.

3.2 Related feature

Guest Authorization

3.3 Flow of events

Code	Feature	User Action	System Response
SC 3.1	None	The guest request access to the home at the main entrance.	The system asks the guest name and the reason for requesting access to the house.
SC 3.2	None	The guest fills in the requested information.	The system takes a guest photograph and sends one message to the home owner mobile device.
SC 3.3	None	-	The system asks for the guest to wait a few minutes.
SC 3.4	None	The home sends an authorization allowing the guest to enter into the house.	The system receives the authorization message.
SC 3.5	None	-	The system displays the message of successful authorization.
SC 3.6	None	-	The system opens the front door and register the occurrence.
SC 3.7	None	-	After \$Time to Close, the front door is closed.

4 Scenario SC04

4.1 Description:

Detect an attempt to intrude the house.

4.2 Related feature

Intrusion Detection

4.3 Flow of events

Code	Feature	User Action	System Response
SC 4.1	Emit Sound Alarm	The presence sensor identifies that someone (or something) is trying to intrude into the smart home. This might be deduced by observing any suspect event (forcing or braking) in the external doors and windows	The system emits the configured internal sound alarm.
SC 4.2	Place a Phone Call	-	The system places a call to the police department.
SC 4.3(A)	Lock Doors	-	The system locks the access to the bedrooms.
SC 4.4(A)	Switch the lights on	-	The system turns on the external and internal lights.

5 Scenario SC05

5.1 Description:

Detect smoke or high variances of temperature inside the smart home

5.2 Related feature

Fire Detection

5.3 Flow of events

Code	Feature	User Action	System Response
SC 5.1	None	The fire sensor identifies a possible fire occurrence (based on smoke or temperature variation).	The system emits the configured internal sound alarm.
SC 5.2	None	-	The system places a call to the fire guard department.